

452 PEL 1000



(non binding picture)

Composition

- 1 scoreboard
- 1 control console
- 1 carrying case for control console
- 1 mains cable (5m)
- Junction box and transmission cables (for cable controlled version)
- Operating and installation instructions

Description

Use:	Indoor	
Transmission:	Radio (868 MHz) or cable	
Readability:	90m, angle >160°	
Dimensions:	1700 x 1000 x 90mm	
Weight:	25 kg	
Power supply:	230V / 50-60Hz	Power consumed: 98 VA
Integrated horn:	116 dB at 1 m	
Protection:	Unbreakable mat polycarbonate front face (DIN 18032-3)	
Mains cable (supplied):	5 m – Type: 230V, 3G, 0.75 mm ²	
Cable controlled:	For cable controlled models or radio controlled models with cable set: Junction Box + 50 m transmission cable (scoreboard/junction box) – Type: phone cable 2 pairs 6/10th + 10 m transmission cable DIN/DIN (junction box/console)	

Display functions

Score :	2 red LED digits (20 cm) – Red Team score from 0 to 99 2 yellow LED digits (20 cm) – Blue team from 0 to 99 Blinking digits for the winning team
Timer:	4 white digits + 2 blinking digits
Game points:	2 green LED digits – points to achieve
Teams:	Red and blue stickers
Service side:	1 red LED arrow (for red team) + 1 yellow LED arrow (for blue team)
Time out:	2 red LED indicator (for red team) 2 yellow LED indicator (for blue team)

Control consoles

- 1 console:** (340 x 175 x 60 mm) with LCD screen with 2 lanes of 20 characters (9mm high)
- 1 charger (radio):** Hold the consoles in charge when there are not in use. (Autonomy max 16 h)
- USB Port:** For program update or connect PC keyboard
- Programme:** Pelota (game programmable in points or sets) - Fronton
- Multilingual Programme**

Options

- TV Interface (RS 485):** Data transmission for TV broadcasting
- Cable set:** Cable mode for radio controlled scoreboard
- Wheeled stand**
- Hand held remote control:** for points

